

K55 Hardware Kit Includes:

#10 Wall Anchor #10 x 1-1/4 Tamper Screw T25 Tamper Torx Bit Mounting Template (4) 900-01028(4) 900-tamperscrew(AR) 900-tamperbit

Materials/Tools Required:

Tape
Level
Pencil
Tape Measure
Hammer
Drill with 7/32" drill bit


Recommended Cleaning Materials

Lint Free Cloth or Wipes Fantastik® All-Purpose Heavy Duty Cleaner

Step 1


K55 - Tamper Screw Mount Installation

Tape template on wall at desired location, using a level to ensure template is level/plumb.




Step 2

At center of hole marks in template drill 7/32" diameter holes




Step 3:

Remove template from wall, deburr holes, and install #10 anchors into wall, using hammer to drive anchors into holes and seat flush to wall.



Sten 4

Carefully position sign to wall, aligning holes in sign with anchors in wall. Using drill with Tamper Torx Bit, install sign to wall using sheet metal screws from front to secure sign to wall.



Sten 5

Remove finger prints from sign face and edges using recommended cleaning materials. DO NOT scrub when cleaning sign. DO NOT use ammonia or abrasive materials.

